

USER INSTRUCTION

WIFI RGBWW LED Controller



I. Product Parameter:

Category	LED Controller
Domination Principle	WiFi
APP	Magic Home Pro
Part Number	W-RGBWW
Operation Platform	Android 4.0 or iOS 9.0 or later
Channels	RGBWW
Input Voltage	DC12-24V
Max Output Power	240W
Connect Method	Common Anode
Working Temperature	-20~+50°C
Control Distance	Visible distance 30M
Certification	CE, RoHS, FCC
Net Weight	38.5g
Dimension(L*B*H)	65MM*194MM*28MM
Carton Size(L*B*H)	49CM*34CM*22CM
QTY Per Carton	100Sets/CTN
Gross Weight	7.8kg

-1-

II. Wire Connection



The connection between the controller and the power supply



Controller and device connection



-2-

III. Instructions

How to connect the controller to Wi-Fi network?

Before Setting/Install the APP:

a) Search for "Magic Home Pro" on the App store or Google Play Store, or scan the QR code to download it; b) (Important) Connect your phone to home wifi network (2.4GHz wifi only); c) Power on the device.

New Setting:

a) Register/Login your Magic Home account.



b) Open the App and Click on "+" button on top right corner, then select "connect device to Wi-Fi network".




-3-

c) Open phone Wi-Fi interface and connect to the "LEDnetxxxx" signal. (If can't find, please reset your controller, turn it on/off for 3 times). After successful connection, go back to the Magic Home Pro APP.



-4-

e) Long press device name to change device type.



-5-

Scan the below QR code to download Magic Home free APP.



APP


If there are any other questions, please scan the below QR code to see more detail operations.



Instruction

-6-

d) Connect to your home network. Select your home network in the Wi-Fi list and enter the correct Wi-Fi password. Then enter the device name and click on "complete".



-4-